

NEMA Sizes 4, 5 and 6—See Contactor/Starter Nameplate to Determine Series A1 or B1

Description		NEMA Size 4 Series A1 Part Number	NEMA Size 4 Series B1 Part Number	NEMA Size 5 Series A1 Part Number	NEMA Size 5 Series B1 Part Number	NEMA Size 6 Series A1 Part Number	NEMA Size 6 Series B1 Part Number
Renewal Parts Publication Number		20428	20428	20429	20429	20146	20146
Contact Kits							
Two-pole		6-44	6-26	6-45	6-45	6-601-2	6-648
Three-pole		6-44-2	6-26-2	6-45-2	6-45-2	6-601	—
Magnet Coils	Coil Suffix						
120V, 60 Hz or 110V, 50 Hz	A	9-1891-1	9-1891-1	9-1891-1	9-1891-1	9-2698	9-2698
240V, 60 Hz or 220V, 50 Hz	B	9-1891-2	9-1891-2	9-1891-2	9-1891-2	9-2698-2	9-2698-2
480V, 60 Hz or 440V, 50 Hz	C	9-1891-3	9-1891-3	9-1891-3	9-1891-3	9-2698-3	9-2698-3
600V, 60 Hz or 550V, 50 Hz	D	9-1891-4	9-1891-4	9-1891-4	9-1891-4	9-2698-4	9-2698-4
208V, 60 Hz	E	9-1891-13	9-1891-13	9-1891-13	9-1891-13	9-2698-5	9-2698-5
277V, 60 Hz	H	9-1891-26	9-1891-26	9-1891-26	9-1891-26	—	—
208/240V, 60 Hz	J	—	—	—	—	—	—
240V, 50 Hz	K	9-1891-20	9-1891-20	9-1891-20	9-1891-20	—	—
380–415V, 50 Hz	L	—	—	—	—	9-2698-6	9-2698-6
380V, 50 Hz	L	9-1891-14	9-1891-14	9-1891-14	9-1891-14	—	—
415V, 50 Hz	M	9-1891-21	9-1891-21	9-1891-21	9-1891-21	—	—
550V, 50 Hz	N	9-1891-8	9-1891-8	9-1891-8	9-1891-8	—	—
24V, 60 Hz–24V, 50 Hz	T	—	—	—	—	—	—
24V, 60 Hz	T	9-1891-15	9-1891-15	9-1891-15	9-1891-15	—	—
24V, 50 Hz	U	9-1891-16	9-1891-16	9-1891-16	9-1891-16	—	—
32V, 50 Hz	V	9-1891-27	9-1891-27	9-1891-27	9-1891-27	—	—
48V, 60 Hz	W	—	—	—	—	9-2698-8	9-2698-8
48V, 50 Hz	Y	9-1891-18	9-1891-18	9-1891-18	9-1891-18	—	—
Overload Relays							
For replacement on existing starters three-pole—ambient compensated bimetallic		10-6530-4	10-6530-4	C306DN3B	C306DN3B	C306DN3B	C306DN3B
Current Transformer							
For replacement on existing starters only		—	—	42-3564	42-3564	42-3598	42-3598
Magnet Frame Armature							
Lower magnet frame		48-1030-2	48-1030-2	48-1030-2	48-1030-2	—	—
Upper magnet frame		48-1029-4	48-1029-4	48-1029-4	48-1029-4	—	—