

Design (continued)

Product overview with information on combinable ET 200M modules and connection cables

MTA type	Input/output area	Article No. of MTA and accessories	Article No. of ET 200M module	Article No. of connecting cable	I/O redundancy
8 channels, AI	1 ... 5 V; ± 5 V; ± 10 V; 0 ... 20 mA; 4 ... 20 mA; ± 20 mA	6ES7 650-1AA52-2XX0 ¹⁾	6ES7 331-7NF00-0AB0 (from product version 5)	6ES7 922-3BD00-0BA0 (3 m) 6ES7 922-3BJ00-0BA0 (8 m)	Yes
8 channels, AI	1 ... 5 V; ± 5 V; ± 10 V; 0 ... 20 mA; 4 ... 20 mA; ± 20 mA	6ES7 650-1AA52-2XX0 ¹⁾	6ES7 331-7NF10-0AB0 (from product version 8)	6ES7 922-3BD00-0BB0 (3 m) 6ES7 922-3BJ00-0BB0 (8 m)	Yes
8 channels, AO	0 ... 20 mA; 4 ... 20 mA	6ES7 650-1AB51-2XX0	6ES7 332-5HF00-0AB0 (from product version 3)	6ES7 922-3BD00-0AS0 (3 m) 6ES7 922-3BJ00-0AS0 (8 m)	Yes
8 channels, AI HART	0 ... 20 mA (without use of HART) 4 ... 20 mA (with/without use of HART)	6ES7 650-1AA61-2XX0 ¹⁾	6ES7 331-7TF01-0AB0	6ES7 922-3BD01-0AM0 (3 m) 6ES7 922-3BJ01-0AM0 (8 m)	Yes
8 channels, AO HART	0 ... 20 mA (with/without use of HART) 4 ... 20 mA (with/without use of HART)	6ES7 650-1AB61-2XX0	6ES7 332-8TF01-0AB0	6ES7 922-3BD01-0AM0 (3 m) 6ES7 922-3BJ01-0AM0 (8 m)	Yes
8 channels, AI TC	Thermocouple types B, C, N, E, R, S, J, L, T, K, U	6ES7 650-1AF51-2XX0	6ES7 331-7PF10-0AB0 (from product version 4) or 6ES7 331-7PF11-0AB0	6ES7 922-3BD00-0AS0 (3 m) 6ES7 922-3BJ00-0AS0 (8 m)	No
8 channels, AI RTD	Resistance thermometers Pt100, Pt200, Pt500, Pt1000, Ni100, Ni120, Ni200, Ni500, Ni1000, Cu10	6ES7 650-1AG51-2XX0	6ES7 331-7PF00-0AB0 (from product version 8) or 6ES7 331-7PF01-0AB0	6ES7 922-3BD00-0AS0 (3 m) 6ES7 922-3BJ00-0AS0 (8 m)	No
16 channels, DO	24 V DC, 0.5 A	6ES7 650-1AD11-2XX0	6ES7 322-8BH10-0AB0	6ES7 922-3BD00-0AT0 (3 m) 6ES7 922-3BJ00-0AT0 (8 m)	Yes
6 channels F-AI HART (safety-related)	0 ... 20 mA (without use of HART); 4 ... 20 mA (with/without use of HART)	6ES7 650-1AH62-5XX0 ¹⁾	6ES7 336-4GE00-0AB0	6ES7 922-3BD00-0AU0 (3 m) 6ES7 922-3BJ00-0AU0 (8 m)	Yes
16 channels, DI	24 V DC	6ES7 650-1AC11-3XX0	6ES7 321-7BH01-0AB0 (from product version 2)	6ES7 922-3BD01-0AM0 (3 m) 6ES7 922-3BJ01-0AM0 (8 m)	Yes
24 channels F-DI (safety-related)	24 V DC	6ES7 650-1AK11-7XX0	6ES7 326-1BK00-0AB0, 6ES7 326-1BK01-0AB0 or 6ES7 326-1BK02-0AB0	6ES7 922-3BD00-0AS0 (3 m) 6ES7 922-3BJ00-0AS0 (8 m)	Yes
10 channels F-DO (safety-related)	24 V DC, 2 A	6ES7 650-1AL11-6XX0	6ES7 326-2BF01-0AB0 (from product version 2) or 6ES7 326-2BF10-0AB0	6ES7 922-3BD00-0AN0 (3 m) 6ES7 922-3BJ00-0AN0 (8 m)	Yes
16 channels DO relay	120 ... 230 V AC, 5 A; 24 V DC, 5 A	6ES7 650-1AM30-3XX0	6ES7 322-8BH01-0AB0 or 6ES7 322-8BH10-0AB0	6ES7 922-3BD00-0AS0 (3 m) 6ES7 922-3BJ00-0AS0 (8 m)	Yes
10 channels F DO relays (safety-related)	120 ... 230 V AC, 5 A; 24 V DC, 5 A	6ES7 650-1AM31-6XX0	6ES7 326-2BF01-0AB0 (from product version 2) or 6ES7 326-2BF10-0AB0	6ES7 922-3BD00-0AS0 (3 m) 6ES7 922-3BJ00-0AS0 (8 m)	Yes

¹⁾ These new terminal modules can no longer deliver a 24 V DC current for feeding 4-wire transmitters. You require an additive terminal module MTA power supply 24 V DC (Order No. 6ES7 650-1BE10-3XX0) if you wish to continue supplying 4-wire transmitters centrally per MTA and redundant with 24 V DC.

Process I/O

Terminal modules

MTA terminal modules

Ordering data	Article No.	Article No.	
MTA terminal modules for SIMATIC PCS 7			
MTA AI terminal module, 8-channel Terminal module for connection of field devices/sensors to a single or two redundant ET 200M analog input modules 6ES7331-7NF00-0AB0 or 6ES7331-7NF10-0AB0 Input range: 1 to 5 V; ± 5 V; ± 10 V und 0/4 ... 20 mA; ± 20 mA Note: 4-wire devices must be supplied separately with current.	6ES7650-1AA52-2XX0	MTA F-AI HART terminal module, 6-channel Terminal module for connection of field devices/sensors to a single or two redundant safety-related ET 200M analog input modules 6ES7336-4GE00-0AB0 Input range: 0 ... 20 mA (without use of HART), 4 ... 20 mA (with/without use of HART) Note: 4-wire devices must be supplied separately with current.	6ES7650-1AH62-5XX0
MTA AO terminal module, 8-channel Terminal module for connection of field devices/actuators to a single or two redundant ET 200M analog output modules 6ES7332-5HF00-0AB0 Output range: 0/4 ... 20 mA	6ES7650-1AB51-2XX0	MTA DI terminal module, 16-channel Terminal module for connection of field devices/sensors to a single or two redundant ET 200M digital input modules 6ES7321-7BH01-0AB0 Input range: 24 V DC	6ES7650-1AC11-3XX0
MTA AI HART terminal module, 8-channel Terminal module for connection of field devices/sensors to a single or two redundant ET 200M analog input modules 6ES7331-7TF01-0AB0 Input range: 0 ... 20 mA (without use of HART), 4 ... 20 mA (with/without use of HART) Note: 4-wire devices must be supplied separately with current.	6ES7650-1AA61-2XX0	MTA F-DI terminal module, 24-channel Terminal module for connection of field devices/sensors to a single or two redundant safety-related ET 200M digital input modules 6ES7326-1BK00-0AB0, 6ES7326-1BK01-0AB0 or 6ES7326-1BK02-0AB0 Input range: 24 V DC	6ES7650-1AK11-7XX0
MTA AO HART terminal module, 8-channel Terminal module for connection of field devices/actuators to a single or two redundant ET 200M analog output modules 6ES7332-8TF01-0AB0 Output range: 0 to 20 mA (with/without use of HART), 4 ... 20 mA (with/without use of HART)	6ES7650-1AB61-2XX0	MTA F-DO terminal module, 10-channel Terminal module for connection of field devices/actuators to a single or two redundant safety-related ET 200M digital output modules 6ES7326-2BF01-0AB0 or 6ES7326-2BF10-0AB0 Output range: 24 V DC, 2A	6ES7650-1AL11-6XX0
MTA AI TC terminal module, 8-channel Terminal module for connection of field devices/sensors to a single ET 200M analog input module 6ES7331-7PF10-0AB0 or 6ES7331-7PF11-0AB0 Input range: Thermocouple types B, C, N, E, R, S, J, L, T, K, U	6ES7650-1AF51-2XX0	MTA DO Relay terminal module, 16-channel Terminal module for connection of field devices/actuators to a single or two redundant ET 200M digital output modules 6ES7322-8BH01-0AB0 or 6ES7322-8BH10-0AB0 Output range: 120 to 230 V AC, 5 A; 24 V DC, 5 A	6ES7650-1AM30-3XX0
MTA AI RTD terminal module, 8-channel Terminal module for connection of field devices/sensors to a single ET 200M analog input module 6ES7331-7PF00-0AB0 or 6ES7331-7PF01-0AB0 Measuring range: Resistance thermometers Pt100, Pt200, Pt500, Pt1000, Ni100, Ni120, Ni200, Ni500, Ni1000, Cu10	6ES7650-1AG51-2XX0	MTA F-DO Relay terminal module, 10-channel Terminal module for connection of field devices/actuators to a single or two redundant safety-related ET 200M digital output modules 6ES7326-2BF01-0AB0 or 6ES7326-2BF10-0AB0 Output range: 120 to 230 V AC, 5 A; 24 V DC, 5 A	6ES7650-1AM31-6XX0
MTA DO terminal module, 16-channel Terminal module for connection of field devices/actuators to a single or two redundant ET 200M digital output modules 6ES7322-8BH10-0AB0 Output range: 24 V DC, 0.5 A	6ES7650-1AD11-2XX0		

Process I/O

SIMATIC ET 200M for SIMATIC PCS 7

F digital/analog modules

Ordering data	Article No.	Article No.
SM 326 F-DI safety-related digital input module, for floating contacts 24 inputs, 24 V DC 80 mm wide Isolated in groups of 12 Redundancy optional (channel-granular redundancy) <ul style="list-style-type: none"> • 4 short-circuit-proof sensor power supplies, each for 6 channels, isolated in groups of 3 • External sensor power supply possible • SIL 2: 1001 evaluation, 24 channels • SIL 3: 1002 evaluation on the module, 12 channels (adjustable discrepancy time) • SIL 3 achievable without isolating module • Short-circuit monitoring to L+ • Discrepancy monitoring • Supports 20 ms time stamping (SOE) • Module internal diagnostics • PROFI-safe telegram • Front connector required: 40-pin 	6ES7326-1BK02-0AB0	
8 inputs, NAMUR [EEEx ib]¹⁾ 80 mm wide Isolated by channel Redundancy optional (channel-granular redundancy) <ul style="list-style-type: none"> • 8 short-circuit-resistant sensor power supplies, each for 1 channel, mutually isolated • SIL 2: 1001 evaluation, 8 channels • SIL 3: 1002 evaluation on the module, 4 channels (adjustable discrepancy time) • Wire break and short-circuit monitoring (for contacts with external resistor circuit) • Discrepancy monitoring • Module internal diagnostics • PROFI-safe telegram • Front connector required: 40-pin 	6ES7326-1RF01-0AB0	
Safety-related digital output module SM 326 F-DO Suitable for solenoid valves, DC contactors and indicator lights		
10 outputs, 24 V DC, 2 A 40 mm wide Isolated in groups of 5 (outputs with internal diode) Redundancy optional (channel-granular redundancy) <ul style="list-style-type: none"> • 10 outputs, isolated in groups of 5 • SIL 3 achievable without isolating module • P/P-switching (for non-floating loads; ground and earth connected together) • Wire break and short-circuit monitoring • Configurable diagnostics • "Keep last valid value" parameter • Channel-selective passivation • PROFI-safe telegram • Front connector required: 40-pin 	6ES7326-2BF10-0AB0	
8 outputs, 24 V DC, 2 A 80 mm wide Electrically isolated in groups of 4 <ul style="list-style-type: none"> • SIL 2, SIL 3 configurable (8 channels) • SIL 3 achievable without isolating module • P/M-switching (for floating loads; ground and earth separate) • Wire break and short-circuit monitoring • Module internal diagnostics • PROFI-safe telegram • Front connector required: 40-pin 	6ES7326-2BF41-0AB0	
		SM 336 F-AI HART safety-related analog input module 6 inputs, 0 ... 20 mA or 4 ... 20 mA 40 mm wide Electrically isolated in groups of 3 Redundancy optional (channel-granular redundancy) <ul style="list-style-type: none"> • Resolution: 15 bits + sign • 2-wire or 4-wire connection • 6 short-circuit-proof sensor supplies for 1 channel each • External sensor power supply possible • SIL 3: 1001 evaluation (6 channels) and 1002 evaluation (3 channels) on the module • SIL 3 achievable without isolating module • Discrepancy monitoring with 1002 evaluation (adjustable discrepancy time) • Wire break monitoring • Module and channel diagnostics • HART communication in measuring range 4 ... 20 mA (can be switched on/off online) • HART status display • PROFI-safe telegram • Front connector required: 20-pin Options Isolating module For F modules, 40 mm wide <ul style="list-style-type: none"> • For isolation of F and standard modules in an ET 200M rack • For signal isolation when using a copper bus connection (only F modules in a rack with IM 153-2) Isolating bus module 80 mm wide, for isolating module, when using an active backplane bus
		6ES7336-4GE00-0AB0
		6ES7195-7KF00-0XA0
		6ES7195-7HG00-0XA0

¹⁾ Module is not PROFINET-enabled