

## Concrete/masonry boxes and accessories

### Shallow masonry boxes



1-MBS



2-MBS



3-MBS



4-MBS



MBPS

#### Shallow masonry boxes

Cat. No.	Depth (in.)	Capacity (cu. in.)	Description	Std. Ctn.
1-MBS	2 1/2	16.5	<b>A one-gang masonry box, 2 1/2" deep x 3 3/4" long x 1 7/8" wide</b> Six 1/2" and two 3/4" concentric KOs. Two in each side and one in each end. Uses Steel City® 100 cover.	10
2-MBS	2 1/2	33.0	<b>A two-gang masonry box, 2 1/2" deep x 3 3/4" long x 3 3/4" wide</b> Eight 1/2" and two 3/4" concentric KOs. Two in each side and two in each end. Uses Steel City® SB-2 cover.	10
3-MBS	2 1/2	49.0	<b>A three-gang masonry box, 2 1/2" deep x 3 3/4" long x 5 1/2" wide</b> Ten 1/2" and 3/4" concentric KOs. Three in each side and two in each end. Uses Steel City® SB-3 cover	5
4-MBS	2 1/2	67.0	<b>A four-gang masonry box, 2 1/2" deep x 3 3/4" long x 7 3/8" wide</b> Twelve 1/2" and 3/4" concentric KOs. Four in each side and two in each end. Uses Steel City® SB-4 cover.	5
MBPS	2 1/2	-	<b>Masonry box partition, 2 1/2" deep x 3 3/4" wide</b> A low-voltage partition drilled and tapped for mounting. Furnished with two 8/32 screws. For use with 2-MBS, 3-MBS or 4-MBS boxes	50

### Deep masonry boxes



1-MB



2-MB



3-MB



4-MB



MBP

#### Deep masonry boxes

Cat. No.	Depth (in.)	Capacity (cu. in.)	Description	Std. Ctn.
1-MB	3 1/2	23.3	<b>One-gang masonry box, 3 1/2" deep x 3 3/4" long x 1 7/8" wide</b> Eight 1/2" and 3/4" concentric KOs. Two in each side and two in each end. Uses Steel City® 100 series covers.	10
2-MB	3 1/2	46.8	<b>Two-gang masonry box, 3 1/2" deep x 3 3/4" long x 3 3/4" wide</b> Twelve 1/2" and 3/4" concentric KOs. Four in each of two sides and two in each end. Uses Steel City® SB-2 cover.	10
3-MB	3 1/2	69.5	<b>Three-gang box, 3 1/2" deep x 3 3/4" long x 5 1/2" wide</b> Sixteen 1/2" and 3/4" concentric KOs. Six in each of two sides and two in each end. Uses Steel City® SB-3 cover	5
4-MB	3 1/2	92.0	<b>Four-gang masonry box, 3 1/2" deep x 3 3/4" long x 7 3/8" wide</b> Twenty 1/2" and 3/4" concentric KOs. Eight in each of two sides and two in each end. Uses Steel City® SB-4 cover.	5
MBP	3 1/2	-	<b>Masonry box partition, 3 1/2" deep x 3 3/4" wide</b> A low-voltage partition drilled and tapped for mounting. Furnished with two 8/32 screws. For use with 2-MB, 3-MB or 4-MB boxes.	50