



18.8

**MLFB-Ordering data :**                   **2KJ3108-9JA02-0FC1-Z**  
**D01+H08+H1G+K06+L02+L68+Y00**  
**{Y00:\*ANL@11\*|\*AND@1500\*}**

Client order no. :

Order no. :

Offer no. :

Remarks :

Item no. :

Consignment no. :

Project :

### Gearbox

<b>Type designation</b>	SIMOGEAR ZF89-K2-(160)
<b>Gearbox</b>	Helical gearbox ZF89
<b>Mounting type gearbox</b>	Flange-mounted design
<b>Output shaft</b>	VG50 x 100 mm (Solid shaft without feather key)
<b>Mounting position</b>	(D01) M1
<b>Transmission ratio</b>	5.26 (2,542 / 483)
<b>Nominal torque</b>	1,060.00 Nm
<b>Output speed</b>	285.171 rpm
<b>Output torque</b>	368.38 Nm
<b>Service factor</b>	2.88
<b>Gear oil</b>	(K06) Mineral oil CLP VG220
<b>Oil charge</b>	2.2 l
<b>Specification</b>	CE (Europe / other countries)
<b>Environment temperature</b>	-15 ... +40 °C
<b>Weight without oil</b>	109.5 kg
<b>Housing material first gearbox</b>	Cast iron

### Gearbox options

<b>Flange diameter</b>	(H08) 350 mm
<b>Output shaft bearing</b>	Standard bearing
<b>Output shaft sealing</b>	Standard sealing
<b>Gearbox breather</b>	Pressure breather valve
<b>Oil level control</b>	Oil level screw
<b>Oil drain</b>	Oil drain plug

### Adapter

<b>Adapter</b>	K2 Coupling adapter for IEC motors
<b>Hole circle</b>	300 mm
<b>Centering</b>	250 mm
<b>Motor shaft</b>	42 x 110 mm
<b>Input speed (Info)</b>	1500 rpm
<b>Input power (Info)</b>	11.00 kW
<b>Input torque</b>	70.0 Nm
<b>Max. perm. input torque for continuous duty T1perm</b>	153.0 Nm
<b>Max. perm. input torque for short-time duty</b>	382.5 Nm
<b>Max. perm. input speed</b>	4,500.0 rpm

### Adapter options

-

### General options

<b>Surface treatments</b>	Painted
<b>Coating</b>	(L02) Coating for normal environmental stress C1
<b>RAL Color</b>	(L68) 5010 gentain blue
<b>Coating on flange</b>	-
<b>Packing</b>	Standard packing

### Further information

<b>General product information</b>	<a href="#">SIMOGEAR</a>
<b>Configurator</b>	<a href="#">2KJ.....</a>
<b>Operating instructions</b>	
<b>Gearbox</b>	<a href="#">BA 2030</a>
<b>Adapter</b>	<a href="#">BA 2039</a>
<b>Catalog</b>	<a href="#">MD 50.11</a> Gearboxes with adapter